

# SO-TXFP-10G-ZR-DWDM-A

XFP, 10G Multirate, DWDM, 50GHz Tunable, 25dB, 80km, D9135-D9610 (96ch)

## OVERVIEW

The SO-TXFP-10G-ZR-DWDM-A is a high performance DWDM XFP-transceiver that is tunable to 96 channels in the 50GHz C-band grid as specified in ITU-T 694.1.

The mechanical characteristics are compliant with the XFP MSA-specification. Wavelength and frequency tuning modes are supported in accordance with SFF-8477.

The transceiver supports data rates from 9.95 to 11.3 Gbps, covering a series of Ethernet, OTN, SDH/SONET and other protocols.

This transceiver provides digital diagnostic functions via a 2-wire serial interface as defined by the INF 8077i specification. The transceiver module is compliant to RoHS-6/6.

## TECHNICAL DATA

Parameter	Value
Technology	DWDM 100GHz XFP
Transmission media	SM (2x LC)
Typical reach	80km
Nominal wavelength	191.35 - 196.10THz (96ch)
Bit rate support	9.95Gbps to 11.1Gbps
Interface standards	10GBASE-ER, 10GBASE-EW
Protocol support	10GbE-LAN, 10GbE-WAN
	OTU2, OTU2e
	STM-64/OC192
	10G FC
	CPRI Opt, 8
Power budget	8 – 25dB
Dispersion tolerance	1600ps/nm
Dispersion penalty	Max 2dB
Power consumption	< 2.5W
Operating temperature	-5°C to +70°C
Storage temperature	-40°C to +85°C

Parameter	Value
<b>Transmitter data:</b>	
Output power	Min: -1.0dB <sup>1)</sup> Max: +3.0dBm <sup>1)</sup>
Transmit wavelength	191.35 - 196.10THz, 50GHz (G.694.1)
Tuning speed	< 50ms
<b>Receiver data:</b>	
Minimum input power	-26.0dBm <sup>1) 2)</sup>
Overload (max power)	-5.0dBm <sup>1) 2)</sup>
Wavelength range	1525nm – 1575nm
LOS assert	Min -33dBm
LOS de-assert	Max -26.5dBm
LOS Hysteresis	Min 0.5dB
DDM	Yes
MSA compliance	INF-8077i, XFP-MSA

<sup>1)</sup> Average power.

<sup>2)</sup> @ 10.7Gbps, BER 1x10<sup>-12</sup>, PRBS 2<sup>31</sup>-1, OSNR> 35dB

### Safety/regulatory compliance:

TUV/UL/FDA (contact Smartoptics for latest certification information)

RoHS compliance

### System performance

Parameter	Min	Max	OSNR	BER	Remarks
Noise loaded	-400ps/nm	1500ps/nm	19 dB	1E-04	10.709Gb/s, -10 to -20dBm, 0.25nm filter BW
Unamplified links	0ps/nm	1600ps/nm	>35 dB	1E-12	10.709Gb/s, -22dBm, 0.25nm filter BW

Subject to change without notice.

For more information visit [smartoptics.com](http://smartoptics.com).

## ORDERING INFORMATION

Ordering code	Description
SO-TXFP-10G-ZR-DWDM-A	XFP, 10G Multirate 9.95-11.35Gbps, DWDM 50GHz Tunable, 191.35 - 196.10 THz (96ch), 80km, 25dB, LC

## GENERAL DEFINITIONS

Parameter	Description
Technology	Grey; Transceiver type for non-WDM applications. Electrical or optical. CWDM; Transceiver type for CWDM applications using G.694.2 channel grid. DWDM; Transceiver type for DWDM applications using G.694.1 channel grid. BiDi; Transceiver pair using two different wavelength channels operating on a single-fiber. DAC: Direct Attach Cable. Electrical cable with attached connectors. AOC: Active Optical Cable. Optical cable with attached connectors.
Transmission Media	Type of fiber, e.g. Multimode (MM) or Singlemode (SM). Number of and connector type within brackets (e.g. 2x LC, 1x MPO).
Typical reach	Nominal distance performance based on typical fiber dispersion, fiber loss and power budget properties, i.e. w/o dispersion compensation and optical amplification. Actual distance is dependent on actual optical path loss and dispersion properties.
Bit rate range	Supported bit rate range in Gigabit or Megabit per second (Gbps or Mbps).
Protocols	Protocols within supported bit rate range.
Nominal wavelength	Typical wavelength(s) from transmitter.
Interface standards	Referenced interface standards or MSA's, e.g. IEEE 802.3 standard for 10GbE services or 100G 4WDM-10 etc.
Power budget	Min and max power budget between Transmitter and Receiver w/o optical path penalties.
Dispersion tolerance/penalty	Maximum amount of tolerated dispersion and required reduction of power budget to maintain stipulated Bit Error Rate (BER) and at a given bit rate.
Temperature range	Max operating case temperature range. Standard temperature range (C-temp): 0°C to +70°C (32°F to +158°F) Extended temperature range (E-temp): typically -20°C to +75°C (-4°F to +167°F) Industrial temperature range (I-temp): -40°C to +85°C (-40°F to +185°F)
Power consumption	Worst case power consumption. Will vary over temperature.
Transmitter Output power	Average output power. Provided in min and max values.
Receiver minimum input power	Minimum average input power at specified BER, normally $1E^{-12}$ . Note that some protocols require FEC to achieve sufficient BER.
Receiver max input power	Maximum average input power giving a BER, normally $1E^{-12}$ .
DDM	Digital Diagnostic Monitoring functionality as defined in e.g. SFF-8472 MSA.

Smartoptics makes no warranties or representations, expressed or implied, of any kind relative to the information or any portion thereof contained in this document or its adaptation or use, and assumes no responsibility or liability of any kind, including, but not limited to, indirect, special, consequential or incidental damages, for any errors or inaccuracies contained in the information or arising from the adaptation or use of the information or any portion thereof. The information in this document is subject to change without notice.